

The Smarter way to Characterize Components



NEW



LCR-8200 Series


High Frequency LCR Meter

- Wide Test Frequency 10Hz ~ 30MHz/20MHz/10MHz/5MHz
- 7" LCD color Display
- 0.08% Basic Accuracy
- Displaying Four Measurement Results Simultaneously From 17 Selectable Measurement Parameters Freely
- 15 Steps List Measurement
- Two Curves Sweep Mode
- Internal DC Bias Voltage $\pm 12V$
- USB Storage Available
- ALC Function Available
- Standard Interfaces : RS-232C, USB Host/Device, LAN, GPIB and Handler
- Universal Power Input



Diverse Meas. Item & Display

Four Displayed items can be selected from 17 measurement parameters freely



Two Curves Graphic

7" color display, under graphic mode is capable to display two parameters sweep curve

www.gwinstek.com

GW INSTEK
Simply Reliable

SPECIFICATIONS				
	LCR-8230	LCR-8220	LCR-8210	LCR-8205
TEST FREQUENCY				
	DC, 10Hz ~ 30MHz; 6 Digits, ±0.0007%	DC, 10Hz ~ 20MHz; 6 Digits, ±0.0007%	DC, 10Hz ~ 10MHz; 6 Digits, ±0.0007%	DC, 10Hz ~ 5MHz; 6 Digits, ±0.0007%
OUTPUT IMPEDANCE				
	25Ω / 100Ω SELECTABLE			
BASIC ACCURACY				
	±0.08%			
TEST SPEED				
	MAX: 2.5ms(>10kHz), FAST: 50ms(>20Hz), MEDIUM: 100ms SLOW: 300ms, SLOW2: 600ms			
TEST SIGNAL LEVEL				
AC Voltage	10mV ~ 2Vrms (FREQ. ≤1MHz), 10mV ~ 1Vrms (FREQ. > 1MHz or FREQ. ≤1MHz and RO=25Ω)			
AC Current	100μA ~ 20mA (RO=100Ω), 400μA ~ 40mA (RO=25Ω)			
DCR Voltage	1Vdc (40mA max.)			
MEASUREMENT PARAMETERS				
	Maximum four parameters can be measured and displayed at the same time Impedance (Z), Inductance (Ls / Lp), Capacitance (Cs / Cp), AC Resistance (Rs / Rp), Quality Factor (Q), Dissipation Factor (D), Admittance (Y), Conductance (G), Reactance (X), Phase Angle ($\theta d / \theta r$), Susceptance (B), DC Resistance (Rdc)			
LIST MEASUREMENT				
Listed Steps	15			
Listed Parameters	Freq/Vac/Iac/DC Bias/Comp/BIN			
Trigger	AUTO, REPEAT, SINGLE			
SWEEP MEASUREMENT				
Swept Graphical	Two of measurement parameters			
Swept Parameters	Freq/Vac/Iac, Keep Trace			
OTHER FUNCTIONS				
Auto Level Control (ALC)	Standard			
DC Bias	0 ~ ±12V			
Handler	PASS, FAIL and OK, NG or BIN 1-9			
OTHER FEATURES				
Correction	Open/Short/HF Load/Load			
V/I Monitor	Vac, Iac, Vdc, Idc			
Comparator	Value, Δ, Δ%			
Buzzer	OFF, Pass, Fail			
Average	1 to 64			
DISPLAY				
	7" LCD color display (800 x 480)			
INTERFACE				
	USB/GPIB/LAN/RS-232/Handler/USB Host/TRIGGER Input			
POWER SOURCE				
	AC 100V~240V, 50/60Hz; Consumption: 65VA (max.)			
DIMENSIONS & WEIGHT				
	346 (W) x 145 (H) x 335 (D) mm; Approx. 3.3kg			

Specifications subject to change without notice. LCR-8000CD1DH

ORDERING INFORMATION	
LCR-8230	DC, 10Hz~30MHz High Frequency LCR Meter
LCR-8220	DC, 10Hz~20MHz High Frequency LCR Meter
LCR-8210	DC, 10Hz~10MHz High Frequency LCR Meter
LCR-8205	DC, 10Hz~5MHz High Frequency LCR Meter
ACCESSORIES	
User Manual (CD) x 1, AC Power Cord x 1, Test Fixture LCR-06B x 1, Safety Sheet x 1	

OPTION ASSESSORIES			
LCR-05	Test Fixture(DIP)	GTL-232	RS232C Cable
LCR-07	Test Fixture(Clip)	GTL-246	USB Cable
LCR-08	Test Fixture(SMD)	GTL-248	GPIB Cable
LCR-12	Test Fixture(Clip)	DC Bias Voltage Box	External DC Bias Voltage Box
LCR-15	Test Fixture(SMD)		
FREE DOWNLOAD			
PC Software	LCR Meter		

Global Headquarters
GOOD WILL INSTRUMENT CO., LTD.
 No.7-1, Jhongsing Road, Tucheng Dist., New Taipei City 236, Taiwan
 T +886-2-2268-0389 F +886-2-2268-0639
 E-mail: marketing@goodwill.com.tw

China Subsidiary
GOOD WILL INSTRUMENT (SUZHOU) CO., LTD.
 No. 521, Zhujiang Road, Snd, Suzhou Jiangsu 215011 China
 T +86-512-6661-7177 F +86-512-6661-7277

Malaysia Subsidiary
GOOD WILL INSTRUMENT (SEA) SDN. BHD.
 No. 1-3-18, Elit Avenue, Jalan Mayang Pasir 3,
 11950 Bayan Baru, Penang, Malaysia
 T +604-6111122 F +604-6115225

Europe Subsidiary
GOOD WILL INSTRUMENT EURO B.V.
 De Run 5427A, 5504DG Veldhoven, THE NETHERLANDS
 T +31(0)40-2557790 F +31(0)40-2541194

U.S.A. Subsidiary
INSTEK AMERICA CORP.
 5198 Brooks Street Montclair, CA 91763, U.S.A.
 T +1-909-399-3535 F +1-909-399-0819

Japan Subsidiary
TEXIO TECHNOLOGY CORPORATION.
 7F Towa Fudosan Shin Yokohama Bldg., 2-18-13 Shin
 Yokohama, Kohoku-ku, Yokohama, Kanagawa,
 222-0033 Japan
 T +81-45-620-2305 F +81-45-534-7181

Korea Subsidiary
GOOD WILL INSTRUMENT KOREA CO., LTD.
 Room No.503, Gyeonginro 775 (Mullae-Dong 3Ga,
 Ace Hightech-City B/D 1Dong), Yeongduengpo-Gu,
 Seoul 150093, Korea.
 T +82-2-3439-2205 F +82-2-3439-2207

India Subsidiary
GW INSTEK INDIA LLP.
 No.2707/B&C, 1st Floor UNNATHI Building,
 E-Block, Sahakara Nagar, Bengaluru-560 092, India
 T +91-80-6811-0600 F +91-80-6811-0626

GW INSTEK
 Simply Reliable



Website



Facebook



LinkedIn